



VID-A1632DC

16 Input to 32 Output Video Distribution Amplifier

Features:

- Wide bandwidth, video gain compensation amplification.
- HF compensation.
 - 10dB adjustable image gain.
 - Sharpness and Brightness adjustment.
- Transmission range: 1000 meters (RG59 coaxial cable)
- Red LED: power on/off.
 - It can be connected to CCTV cameras, multiplexer, VCR, DVR, etc.
- Power Supply: DC12V
- Power Consumption: 480mA
- Dimensions (mm): 483 x 88 x 44mm (59 with BNC) (2U height)
- Weight: 1400 g
- Material: Metal Black

Specification:

- Video Input Channels: 16
- Video Output Channels: 32
- Video Input Level: 0.8-1.2Vp-p, 75 Ohms
- Video Output Level: 1Vp-p (Standard), 75 Ohms
- Video Bandwidth: 10hz - 10MHz

Warranty (Effective Jan 1, 2009)

Limited Lifetime

© Aventura Technologies



- 16 video inputs
- 32 video outputs
- 0.8-1.2Vp-p, 75 Ohms input level
- 1Vp-p (Standard), 75 Ohms output level
- 10hz - 10MHz bandwidth

AVAILABLE MODELS

Part number	Description
VID-A1632DC	16 Input to 32 Output Video Distribution Amplifier